

FBT Products

SP 28 - Signal Audio Selector – 2 IN – 8 OUT

Features:

- Frequency response (@-3 dB) 10 Hz to 20 kHz
- THD + N 0.001%
- Input impedance 22K ohm balanced
- Gain 6 dB
- Signal/noise ratio > 110 dB
- Max input level 20 dB
- CMRR > 50 dB
- Separation between channels (@ 100Hz, 1 kHz, 10kHz) 76 dB, 55 dB, 36 dB
- Max output (@ 10 K ohm) 26 dBu
- Output impedance 600 ohm
- Connectors: XLR-F inputs, XLR-M outputs
- Power supply 230 Vac, 50 Hz
- Dimensions (WxHxD) 482x44x205 mm
- Weight 2.4 kg



Front panel:

- 4 rotary potentiometers separately adjusting the output level of the 4 stereo systems (Left and Right)
- 4 push-buttons, without detent, that activate (LED on) the relevant outputs of the 4 stereo systems (Left and right)
- 1 "Priority" push-button, with detent, to activate the output of the selected system while excluding the previous one
- 1 "Left" push-button, with detent, activating all the outputs associated with the left channel
- 1 "Right" push-button, with detent, activating all the outputs associated with the right channel
- "Power" switch

Rear panel:

- 1 connector to link the external power unit (supplied)
- 2 electronically balanced inputs of the Left and Right channels (XLR-M Neutrik)
- 8 electronically balanced outputs of the 4 stereo systems (XLR-F Neutrik)
- All the inputs and outputs with the Ground-Lift switch