


Tach Products

MF 1000 AM / FM RDS TUNER with LED Backlit Buttons

Features:

- With LED Backlit Buttons
- AM or FM BAND
- Automatic and Manual Tuning
- RDS Function
- Radio Memory Function of 30 presets : FM 1 x 10 / FM 2 x 10 / AM x 10
- * Comes with: -AM Antenna Set x 1 -AV Wire x 1 -Remote Controller x 1
 -FM Antenna Wire x 1 -AC Power Cord x 1



Specifications:

SYSTEM SPECIFICATIONS	
Power Requirements	240V AC / 50Hz or 13.2V DC
Power Consumption	45W
FM-TUNER SPECIFICATIONS	
Tuning Range (RDS)	87.5MHz ~ 108MHz
30dB Quietine Sensitivity	28dB
S/N Ratio at 1mV/m INPUT	46dB
T.H.D at 1mV Input	0.5%
Auto Tuning Sens. (97.9MHz)	28dB ~ 35dB
Output Max	2dB ±1.3V
AM-TUNER SPECIFICATIONS	
Tuning Range	522KHz ~ 1611KHz
20dB Quietine Sensitivity	58dB
S/N Ratio at 5mV/m INPUT	40dB
T.H.D at 1mV Input	0.5%
Auto Tuning Sens. (981KHz)	55dB ~ 85dB
Output Max. (1KHz)	2dB ±1.3V
SPECIFICATION OF AUX IN	
AUX IN TYPE	Stereo
AUX IN & OUTPUT	1:1
DIMENSIONS	
483 (W) X 44 (H) X 215 (D) mm	

* Specifications are subject to change without notice.