

Tach Products

Powered Mixers

TA-120CS/TA-200CS

Powered Mixer with CD player and 5 zone selector



Features:

- ⊙this system has high-quality sound output as good as that of Hi-Fi stereo systems
- ⊙emergency alarm priority function
- ⊙CD player with Japanese parts & remote control
- ⊙USB input for audio input from MP3 player
- ⊙Modular CD player allows easy installation & maintenance from front panel

Specifications:

- Power output : 120W RMS / 200W RMS
- Power Supply: AC 230V 60Hz, DC 24V
- Loaded impedance: 100V.70V.0V, 16Ω.8Ω.4Ω.0Ω.
- Speaker circuit : 5 circuits+ ALL Zone
- Input: MIC × 3, LINE × 3(LINE 1 and LINE2 can be switched to MIC)
- Frequency response : 20Hz ~ 15KHz ± 3dB
- Distortion rate : 0.1% ±5 (1KHz Output)
- Tone control: Bass ± 10dB, Treble ± 10dB
- REC OUT: 1KΩ 0dB
- CD player: Parts from Japan, DC 12V
- Color: Black
- Dimension:420mm(W) × 102mm(H) × 335mm(D)
- Weight:11.1KG/12.3KG