

Tach Products

Powered Mixers

TA-120CT / TA-200CT

120W / 200W Powered Mixer with CD player & Tuner



Features:

- ⊙this system has high-quality sound output as good as that of Hi-Fi stereo systems
- ⊙emergency alarm priority function
- ⊙CD player with Japanese parts and remote control
- ⊙USB input for audio input from MP3 player
- ⊙Modular CD player & Tuner allow easy installation & maintenance from front panel
- ⊙AM/FM Tuner with 10 presets each

Specifications:

- Power output : 120W RMS / 200W RMS
- Power Supply: AC 230V 60Hz, DC 24V
- Loaded impedance : 100V.70V.0V, 16Ω.8Ω.4Ω.0Ω.
- Input: MIC × 3, LINE × 2 (LINE 1、LINE 2 can be switched to MIC)
- Frequency response : 20Hz ~ 15KHz ± 3dB
- Distortion rate : 0.1% ±5. (1KHz Output)
- Tone control: Bass ± 10dB, Treble ± 10dB
- REC OUT : 1KΩ 0Db
- CD player: Parts from Japan, DC 12V
- Tuner: AM Frequency range : 522–1620KHZ, FM Frequency range : 87.5–108MHZ
- Color: Black
- Dimension: 420mm(W) × 102mm(H) × 335mm(D)
- Weight: 11KG/12.2KG