

► DIGITAL CONSOLES

DIGILIVE 16

The DIGILIVE 16 offers ultra-compact digital audio mixer combines the power of a hardware mixer with the beauty and simplicity of a touch-screen control surface.

The DIGILIVE 16 is designed to be quick, simple and intuitive to use. In addition to the 7-inch high-resolution touch-screen where you can access all your features, I/O options and effects, the mixer features full 100mm motorised faders that can recall scene settings at a moments notice. Full control is also available remotely via Wi-Fi using your iPad so you are free to mix anywhere in the venue.



INTELLIGENT USER INTERFACE

- > simple to use 1024 x 600 7" touchscreen with clear and informative graphics
- > clear visual representation of all channel and mixer settings
- > use either touchscreen or encoder to adjust any setting
- > 100mm motorized faders, with one touch layer selection
- > solo, mute and channel select buttons for each channel



MIXING MADE EASY

- > input and output channel metering is clear with the high definition screen
- > both input and output levels clearly displayed
- > pre and post fader metering



RECORDING AND PLAYBACK

- > built in media player and recorder
- > playback from either USB
- > record from any smart output



SMART OUTPUTS

- > 16 internal busses with 8 balanced XLR outputs
- > comprehensive routing facilities to maximise mixer flexibility
- > simple and clear selection and routing



ADVANCED ALGORITHMS

- > 4 band fully parametric EQ
- > each band adjustable between 20Hz and 20kHz
- > variable gain and Q, and ability to save EQ library presets
- > automatic real time analysis (RTA) on 31 band graphic equaliser



DYNAMICS AND EFFECTS ON EVERY CHANNEL

- > fully adjustable gate and compression
- > 4 stereo effects available with reverb, delay, modulation and 31 band graphic EQ
- > simple to use and informative visual representation of effect or dynamic
- > depth and gain reduction metering for accurate adjustment



KEY Features

16 ANALOGUE INPUTS 12 mic input and 2 stereo input channels .

16 INTERNAL busses available .

9 MOTORIZED FADERS for recall and precise control .

8 STEREO FX add reverb, delay, modulation .
or 31 band graphics to busses or channels

8 SMART OUTPUTS each output can be set to any bus .

DIGITAL I/O USB playback/record, S/PDIF in/out and AES-EBU output .

7" TOUCH SCREEN high resolution to clearly see the information you need .

SCENE SAVING complete desk (except gain) settings can be saved .

IPAD CONTROL full remote operation from the IOS APP .

EXTERNAL PSU for reliable noise free operation .

Rear Panel

- built in media player and recorder
- playback from either USB
- record from any smart output



“
With its compact form factor, simple easy to use interface, and wifi connectivity, the DIGILIVE 16 is perfect for gigging musicians and small venues.
”

Specification

MIC Input	12 channels 8 x XLR/4 x COMBO XLR/JACK
LINE Input	2 (Stereo) channels Two 6.5 stereo Jacks, one 3.5 stereo Jack in parallel with one stereo channel
Master Output	2 Left/Right balanced XLR
Smart Outputs	6 assignable balanced XLR
Internal busses	16
Stereo Monitor	1 TRS Jack output
Headphone	1 TRS Jack output
Screen	7" high definition touch screen
Faders	8 x motorized 100 mm faders + 1 x motorized 100mm fader for L/R mix
Sample Frequency	48kHz
AD/DA	192kHz, 24-bit
DSP	40-bit float point, SHARC processor
iPad Remote control	Yes
Effects	up to 8 assignable effect modules (reverb, modulation, delay, 31 band GEQ with RTA)
Digital input/outputs	
AES/EBU	Output (XLR)
S/PDIF	Input / Output (RCA phono)
USB Interface	2 for playback/recording, scene storage and system updates
Network	yes via WIFI external module
Power	90-240V ~ 50/60Hz power supply 24VDC output
Dimension (W x H x D)	357 x 145 x 480mm
Net Weight	5kg