

## PM-04

### Multiple Zone Paging Microphone

#### Features

- ▶ 4 independent zone assign buttons
- ▶ Multi-zone selection possible
- ▶ Powered through 48V DC phantom power
- ▶ On/Off switch for completely defeating mic
- ▶ Perfect for announcements and paging
- ▶ Flexible gooseneck



#### Overview

The Asystems PM-04 paging microphone works in conjunction with the DM434 zone mixers to allow for paging to individual, multiple, or all zones. With 4 independent zone buttons, the microphone's signal can be manually assigned to any individual zone or group of zones as needed. The gooseneck microphone's position can be adjusted to better suit the user's needs. The entire system is powered through the DM434's phantom power and zone control is made through the RJ-12 connector.

## Specifications

Type	Electret Condenser
Pattern	Cardiod
Sensitivity	-55 dB (1kHz, 0dB=1V/Pa)
Frequency Response	40Hz to 16kHz
Signal to Noise Ratio	72dB
Output Impedance	600Ω
Zone Buttons	4
Connectors	XLR, RJ-12
Coverage Zone	20 to 80 cm
Power Supply	+48V DC Phantom Power
Size (W x H x D)	
Weight	0.8 kg (1.8 lbs)

