

Mipro Products

ACT-30T Bodypack Transmitter

Product Features:

- Miniature, compact design.
Lightweight, rugged construction.
- ACT™ syncs the transmitter and receiver frequency automatically.
- Pilotone squelch for interference-free operation.
- Built-in transmitter AF gain adjustment.
- Impedance selectable switch for microphone or guitar.
- Connector for optional MJ-70 remote mute switch cable.
- 4-pin mini XLR connector is compatible with all MIPRO lavalier, headworn microphones and instrument cable.
- Silent on/off switch.
- 4-segment battery status meter.
- LCD displays group, channel, frequency code, AF gain level, mute & lock status & error message code.
- 20-hour battery life per 2 'AA' alkaline batteries.
- 100m(330ft.) operating range.
- 100% made in Taiwan.



Specifications:

Housing	Rugged Plastic
LCD Display	LCD displays working band-code, group, channel, frequency, AF input gain, RF output power, mute & lock status, battery status and error codes.
Oscillation Mode	PLL Synthesized
Frequency Range	UHF 620~934MHz
Bandwidth	24MHz
Channel Set-Up	ACT Sync
RF Output Power	10~50mW (switchable)
Spurious Emissions	<-55dBc
Max. Input Level	0dBV
Microphones	MU-53L
Battery	2 AA alkaline or rechargeable batteries
Dimensions	63(W)×82(H)×22(D)mm / 2.5(W)×3.2(H)×0.9(D)"
Weight	Approx. 83g / 2.9oz (excluding batteries)
Note	Refer to actual product in the event of product discrepancy. Frequency range and maximum deviation comply with the regulations of different countries.