

Tach Products

Powered Mixers

TA-80PA / TA-120PA / TA-200PA 80W / 120W / 200W Powered Mixer



Features:

- ©this system has high-quality sound output as good as that of Hi-Fi stereo systems
- ©emergency alarm priority function

Specifications:

- Power output : 80W RMS / 120W RMS / 200W RMS
- Power Supply: AC 230V 60Hz, DC 24V
- Loaded impedance : 100V.70V.0V, 16Ω.8Ω.4Ω.0Ω.
- Input: MIC × 3, LINE × 3 (LINE1 and LINE2 can be switched to MIC)
- Frequency response : 20Hz ~ 15KHz ± 3dB
- Distortion rate : 0.1% ±5 (1KHz Output)
- Tone control: Bass ± 10dB , Treble ± 10dB
- REC OUT : 1KΩ 0dB
- Color: Black
- Dimension:420mm(W) × 102mm(H) × 335mm(D)
- Weight : 9.7KG/10.9KG