

Tach Products

MF 5200 CD With RDS FM Tuner & Bluetooth Player

Features:

- With LED Backlit Buttons
- Offers USB, SD Card, CD and Tuner & Bluetooth Player function
- Compatible up to 16G USB, SD card/SDHC
- Accepts 12cm disc, such as CD, CD-R, CD-RW, MP3 disc.
- Playing format: MP3, WMA



Specifications:

SYSTEM SPECIFICATIONS	
Power Requirements	240V AC / 50Hz or 24V DC
Power Consumption	45W
CD-PLAYER SPECIFICATIONS	
Frequency Response	± 3dB (100Hz ~ 10KHz)
Separation	>60dB@1KHz
S/N Ratio	>60dB@1KHz
T.H.D Noise	0.3% (1KHz/OUT=1V)
Playing Format	MP3 / WMA
BLUETOOTH SPECIFICATIONS	
Output 0.5V ±2dB	
Frequency Response	± 3dB (100Hz ~ 10KHz)
Separation	>60dB@1KHz
S/N Ratio	>60dB@1KHz
T.H.D Noise	5.0% (1KHz/OUT=0.5V)
FM-TUNER SPECIFICATIONS	
Tuning Range	87.5MHz ~ 108MHz
30dB Quietine Sensitivity	28dB
S/N Ratio at 1mV/m INPUT	46dB
FM Radio Data System (RDS)	
AM-TUNER SPECIFICATIONS	
Tuning Range	522KHz ~ 1611KHz
20dB Quietine Sensitivity	58dB
S/N Ratio at 5mV/m INPUT	35dB
DIMENSIONS	
483 (W) X 44 (H) X 225 (D) mm	

Tach Products

MF 5200 CD With Tuner & Bluetooth Player

Specifications (continued):

LINE OUTPUT:
Max CD3SU RCA OUT 1.0V +/-2db, Dis. 0.3%
XLR OUT 2.0V +/-2db, Dis. 0.3%
FM (Mod. to 45KHz) Output 0.6V +/-2db
AM (Mod. to 45%) Output 0.5V +/-2db

** Specifications are subject to change without notice.*