

## Mipro Products

### ACT-7T Bodypack Transmitter



#### **Features:**

- Sturdy, compact magnesium alloy housing.
- ACT™ syncs the transmitter and receiver frequency automatically.
- Pilotone squelch for interference-free operation.
- Built-in transmitter gain adjustment.
- Impedance selectable switch for microphone or guitar.
- 4-pin mini XLR connector is compatible with all MIPRO lavalier, headworn microphones and instrument cable.
- Silent on/off switch.
- 4-segment battery status meter.
- LCD displays group, channel & error message code.
- 20-hour battery life per 2 'AA' alkaline batteries.
- 100m(330ft.) operating range.
- 100% made in Taiwan.

# Mipro Products

## ACT-7T Bodypack Transmitter

### Specifications:

Oscillation Mode	PLL Synthesized
Frequency Range	UHF 480~934MHz
Bandwidth	24MHz
Channel Set-Up	ACT Sync
RF Output Power	10~30mW (country dependent)
Spurious Emissions	<-55dBc
Max. Input Level	0dBV
Microphones	<a href="#">MU-53L</a> , <a href="#">MU-55L</a> , <a href="#">MU-53HN</a> , <a href="#">MU-55HN</a>
Battery	2 AA alkaline or rechargeable batteries
Dimensions	66(W)×107(H)×25(D)mm / 2.6(W)×4.2(H)×1.0(D)"
Weight	Approx. 120g / 4.2oz (excluding batteries)
Patents & Approvals	Patented. Telecom and safety regulations approved.
Note	Refer to actual product in the event of product discrepancy. Frequency range and maximum deviation comply with the regulations of different countries.

### Microphones:



**MU-53L**

**MU-55L**

**MU-53HN**

**MU-55HN**